# State State

## S-Premium<sup>™</sup> Range

S-Premium<sup>\*\*</sup> is a range extension of the successful S-Click<sup>\*\*</sup> Smart Living range and are specifically designed to be compatible with Clipsal Saturn<sup>\*\*</sup> and Saturn Zen<sup>\*\*</sup> wall plates. The push button dimmers and timers make use of the button already installed in the wall plate, while the rotary dimmers come with a silver knob and chrome ring designed to match the Saturn Zen<sup>\*\*</sup> look. With this range you now have the ability to time 2-Wire and 3-Wire circuits, a feature not currently available in the market.

The S-Premium<sup>™</sup> range includes 2 rotary versions of Digital Dimmer<sup>™</sup>, one with integrated ON/OFF push switch, that feature a blue indicator LED that beautifully matches existing installed switches.

### **COMPATIBLE WITH CLIPSAL SATURN™ WALL PLATES ONLY.**

DIGITAL DIMMER™ RANGE														
Part No.	Description	Indicator Colour	Use with	Integrated ON/OFF Switch	Transformers or Ballasts		Remote	Fans	Additional		Max	Min	Surge	
			Dimmable LED		Electronic	Wire Wound/ Iron Core	Switch Compatible	Compatible	Feature	Max Load	Current (A)	Current (VA)	Rating	Suggested Use
De HNS616DT	Push Button Digital Dimmer <sup>™</sup>	Blue	~	~	~	V 1	×	×	ON/OFF Switch	350W	1.5	10	2kV	Perfect for Dimmable LED lighting
Dg HNS626DT	Rotary Digital Dimmer <sup>™</sup> Switch	Blue	×	~	~	✓ <sup>1</sup>	×	×	ON/OFF Switch	350W	1.5	10	2kV	Perfect for Dimmable LED lighting
De HNS636DT	Rotary Digital Dimmer <sup>™</sup>	Blue	~	×	~	✓ <sup>1</sup>	~	×	Simple	350W	1.5	10	2kV	Perfect for Dimmable LED lighting

#### FANS, MOTORS, COMMERCIAL LIGHTS

Part No.	Description	Max Time Out	Indicator	Remote Switch Compatible	Transformers or Ballasts		Dimmer	Fans	Additional		Max	Min	Surge	
			Colour		Electronic	Wire Wound/ Iron Core		Compatible		Max Load	Current (A)	Current (VA)	Rating	Suggested Use
MJ HNS446TM	Minute Timer 3-Wire	30 Mins	Blue	<b>v</b>	~	<b>v</b>	~	~	Indefinitely On	1200W 500VA	5	0	2kV	Heat Lamps, Fans, Exhaust Fans, Spa Air Pump
HJ HNS456TM	Hour Timer 3-Wire	24 Hours	Amber	×	~	<b>v</b>	<ul> <li>✓</li> </ul>	~	Boost Mode	1200W 500VA	5	0	2kV	Small Pool Pumps, Water Features, Garden & Decorative Lighting



Installation: The modular S-Click<sup>®</sup> range are to be installed as part of a fixed wire electrical installation. By law such installations must be made by a licensed electrical contractor or similarly qualified person. <sup>1</sup> Atco & Clipsal Brand. Saturn<sup>®</sup> is a registered trademark of Schneider Electric Pty. Ltd.

S-Click<sup>®</sup> has a policy of continuous product improvement and reserves the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where available, technical and MSDS data sheets are available on the S-Click<sup>®</sup> website. All S-Click<sup>®</sup> products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to S-Click<sup>®</sup> website for terms and conditions on warranty.



Part No. SPREMIUMCOMPCHRT

#### **COMPATIBLE WITH CLIPSAL SATURN™ WALL PLATES ONLY.**

S-PREMIUM MULTIWAY DIMMING, 3-WIRE TIMERS AND SWITCHING											
	Description	Indicator Colour	Indicator Operation	Additonal	Suggested Use						
RB <sup>®</sup> HNS026RB	Remote Button	Blue	Configurable - Always ON, Always OFF or ON when pressed	LED Indicator Requires Neutral - Button operates without neutral	Use with Dimmer and 3-Wire Timers and Switches Only						

DOMESTIC LIGHTING														
Part No.	Description	Max Time Out	Indicator Colour	Remote Switch Compatible	Transforme Electronic	ers or Ballasts Wire Wound/ Iron Core	Dimmer Compatible	Fans Compatible	Additional Feature	Max Load	Max Current (A)	Min Current (VA)	Surge Rating	Suggested Use
MT HNS416TM	Minute Timer 2-Wire	30 Mins	Blue	<ul> <li></li> </ul>	~	×	×	×	Indefinitely On	400W 400VA	1.7	10	4kV	Lights - Hallway, Garages, Laundries, Wardrobes
HT HNS426TM	Hour Timer 2-Wire	24 Hours	Amber	<ul> <li></li> </ul>	~	×	×	×	Boost Mode	400W 400VA	1.7	10	4kV	Heated Towel Rail (<400W), Heated Mirrors, Security Lighting, Garden & Decorative Lighting

ROUTINE TIMERS														
				Multiway	Transform	ers or Ballasts					Max	Min		
	Description	Max Time Out	Indicator Colour	Switch Compatible	Electronic	Wire Wound/ Iron Core	Dimmer Compatible	Fans Compatible	Additional Feature	Max Load	Current (A)	Current (VA)	Surge Rating	Suggested Use
Rīj <sup>®</sup> HNS716RT	Routine Timer	12 Hours	Red	Yes with Momentary Mains Switch	~	×	×	×	Timer Switch	300W 300VA	1.3	10	2kV	Towel Rails, Security Lighting, Heated Mirrors



Installation: The modular S-Click<sup>®</sup> range are to be installed as part of a fixed wire electrical installation. By law such installations must be made by a licensed electrical contractor or similarly qualified person. <sup>1</sup> Atco & Clipsal Brand. Saturn<sup>®</sup> is a registered trademark of Schneider Electric Pty. Ltd.

S-Click<sup>™</sup> has a policy of continuous product improvement and reserves the right to change materials and specifications without notice. Drawings, where used, are not to scale. All dimensions are in millimetres and sizes given are approximate. Where available, technical and MSDS data sheets are available on the S-Click<sup>™</sup> website. All S-Click<sup>™</sup> products should be installed and used in accordance with manufacturer's instructions provided. Warning: products may be the subject of registered designs and patents. Refer to S-Click<sup>™</sup> website for terms and conditions on warranty.



Part No. SPREMIUMCOMPCHRT